
simex


SWE-73-L

- loop-powered meter in a small case
- measurement input 4-20 mA
- optional alarm output available
- peak values detection



- supply from the current loop,
- detection and visualization of the peak values,
- IR remote controller as accessory.

Examplary pin assignment



Ordering

SWE-73-L-9-XX1

options:00 : no options01 : IP 65

0M: signalization output






e controller

Typical applications

- 1. Indication of current values of any parameters,
- Application wherever there is a need for a quick view of many parameters, i.e. in a synoptic system.



Technical data

Power supply: from measurement line, min. current 3.5 mA, max. voltage drop 7V **Display:** LED, red, 4 x 13 mm high

Input: current 4-20 mA, overload-protected, input current limited to about 50 mA Displayed values range: -999 ÷ 9999 plus decimal point

Accuracy: 0.1% @25°C

Stability: 50 ppm/°C

Output (option): 1 x relay SPDT 30V/500 mA, resistive load, for signalization purpose

only

Data memory: non-volatile memory, EEPROM type Operating temperature: 0°C ÷ +50°C

Storage temperature: -10°C ÷ +70°C

Protection class: IP 40 (front side); IP 65 (front side when an optional seal is

installed); IP 20 (case and connection clips)

Case: board

Case material: NORYL UL94V-0 Case dimensions: 72 x 36 x 77 mm Panel cut-out dimensions: 67 x 32,5 mm

Installation depth: min. 78 mm Board thickness: max. 5 mm

Accessories



IR remote controller SIR-15